

LineBox introduction YouTube [https://youtu.be/ RUxIfTnQx8](https://youtu.be/RUxIfTnQx8)

Please enable YouTube caption setting.

Main Features

1. With LineBox connecting with PBX trunk port, analog phone or office conference phone, employees can use desk phone for a LINE talk. No need headset and microphone! Keep your phone usage habit for LINE calls. Office can save carrier lines.
2. When employees are out of office, they can call back office via free LINE to save expensive roaming or mobile phone fee.
3. Support LINE friends speed dial number and the speed dial list can be exported for back up and imported for use
4. LINE DOD – Call out assigned LINE account automatically when the phone is off hook.
5. LINE DID – Direct forward to the assigned extension for incoming LINE calls for PBX application.
6. Switch between LINE and landline mode by pressing phone key “#”.
7. Switch between a landline call and a LINE call by pressing phone keys “*1” and hang up current call by pressing phone key “*”.
8. Add an interrupt LINE call or an interrupt landline call into a LINE & landline Conference by pressing phone keys “*2”.
9. “Audio recovery” button resolves LINE call party’s problem to hear each other.
10. Support FSK Type 1 like Caller ID and display "LINE 566" or "566" and incoming call time.
11. IM mode as a USB audio device for soft phones like Team, Lync/Skype for business, Google voice/hangouts, WhatsApp, Facebook Messenger, Skype, Zoom, Turn existing analog conference phones as Skype or other soft phone conference phone to enhance conference voice quality.
12. Support popular PBXs and cordless phone including DECT, 5.8GHz, 2.4GHz, 900 MHz, ...
13. Support international busy tone.
14. Support 2 REN standard loads and 20, 25, 30 and 50Hz ring signal frequency.
15. Automatically allow new LINE friend (Default disable).

16. Support LineBox software on line upgrade and latest software version check/download.
17. **LineBox hardware can run recent SkyBox S1 software to work as a Skype**
18. Auto-Detection and Auto-Swap for Line and Phone RJ11 ports when the device starts up.



Normal Wiring



Wrong Wiring but Functional

Minimum System Requirement

- One PC running at 1G Hz or better, 512 MB RAM and one spare USB port
- PC with Microsoft Windows 10, 8, 7 and LINE 6.x or later version

Product Specification

- USB 1.1 plug and play, USB bus power, No external power
- Two RJ-11 ports. One Phone (FXS) port is for standard analog or cordless phone sets (Or standard PBX analog trunk line); the other Line (FXO) port is for traditional landline
- L x W X H: 95 X 66 X 22 mm

Product Application





Contact Information

Regin Technology Corp. LTD.

Office: 886-3-5735360

Fax: 886-3-5739231

Mobile: 886-936071552

Email: henry@regintech.com.tw

Address: 3F, NO. 41, Lane 42, Dongguang Rd., Hsinchu, Taiwan

Web: <https://www.regintech.com.tw>

Skype: regin.skype

LINE: 瑞駿科技 Line (Scan the QR code below or search LINE ID by "regintech")



Regintech Official Website



Regintech Official LINE